

Rotating infantry target "CP"

BAUR SA

Corniche 9
CH-2024 St-Aubin-Sauges

Tél. +41 (0) 32 835 16 55

Fax +41 (0) 32 835 34 69

www.baur.ch

Description:



Rotating infantry target, easy to transport, stationary or mobile, controlled by radio or WiFi. The "CP" is a rugged target system that can be used outdoors allowing representation of friend or enemy target by rotating the target image.

Can be controlled remotely with a CRC4 (radio command unit) or from a central command unit (CCU) equipped with the ciblesCOM software suite (additional functions will then be available).

Movement:

Rotating movement of the target image. Target image is set square to the shooting direction after a hit (neutral position).

Typical use:

Our infantry target systems can be used with real ammunition, simunition and laser simulation.

Type of munition:

Designed to be used with ammunition ranging from 5.56 to 12.7 mm caliber.

Target images:

An universal mounting system allows use of wooden, PE or aluminium target images. Custom made target images can also be used.

Accessories:

All our target systems are equipped with an APP connector for use with different accessories (LOMAH, firing system, etc.)



Target "CP" type CP91

Technical specifications:

Size:	330 x 310 x 230 mm
Weight:	12.5 kg (16.0 kg with battery)
Movements:	< 0.4 s (90° rotation)
Interfaces:	WiFi (WLAN 802.11b) Radio VHF (136-174 MHz) Radio UHF (403-470 MHz)
Battery:	LiPo 12V/ 30Ah NiCd 12V/ 7Ah
Number of cycles (90° rotation) at 20°C:	~5500 (LiPo battery) ~1500 (NiCd battery)
Duration of life:	All our products are built to last 25 years
Reliability tests:	Vibration, shocks, temperature, EMC

Key features:

No maintenance required. Can stay in the field 365 days/year

All the target parameters can be accessed and modified remotely (target ID, sensitivity, radio channel, etc.)

Can be controlled by radio (stand-alone, no CCU required) or WiFi (ciblesCOM software and WiFi coverage required)

Fast rotating movements for challenging friend / enemy situation



Friend



Neutral



Enemy

Accessories:



Fixing and mounting systems



Sound generator



LOMAH



CRC4

Minimum configuration:

- control command unit

Subject to change without notice
© 2006 Baur SA